# TOR-5N

Future Ready Dual Channel Flow and Dual Pressure Data Logger



DUAL CHANNEL FLOW AND DUAL PRESSURE DATA LOGGER FOR MONITORING, RECORDING AND TRANSMITTING THROUGH NB-IOT, LTE-M OR 2G (SMS/GPRS)

# **Applications**

- Leak Detection
- **Network Modelling**
- Flow Monitoring
- **PRV Monitoring**
- **Pressure Monitoring**



T +44 (0) 1837 503381 E sales@ash-eng.com www.ash-eng.com

# **Specifications**

## Power

2x Lithium battery (7.2V, 13Ah) >5 years life under typical usage External battery (optional)

## Memory

16MB Non-volatile 320,000 records Cyclic or Stop when full

#### Inputs

Up to 2 Pulse/Events 1 Event Input

2 Swiss Made Internal Pressure Transducer (0.25%/0.1%)

#### Connectors

2 x Souriau

2 x Standard Quickfit Male Port

#### Modem

NB-IoT/LTE-M with 2G fallback Low Power

# Communications

SMS/Data to server Remote firmware upgrades and configuration Internal antenna

SMA external antenna connection USB to serial configuration

# **Alarms**

Multiple High/Low Fastline and human readable SMS 10 Profile alarms

# Clock

Auto correction on server connection

### **Schedules**

1 second to 24 hour logging intervals Configurable transmission schedules

#### Environmental

IP68 -20°C to 70°C

# Weight

750g

#### Software

TOR Configuration Software AquaGuard - Online Portal

# **Options/Ordering codes**

			А		В
	TOR-5N	-	Χ	-	Χ
No Modem NB-IoT/ LTE- Antenna		L NBE			
5 Bar 10 Bar 20 Bar				A B C	
Examples					
TOR-5N-L-B	No Modem, 3 Digital, 2 Pressure (10 Bar)				
TOR-5N-NBE-B	NB-IoT/ LTE-M Modem, Internal Antenna, 3 Digital, 2 Pressure (10 Bar)				

# **Accessories**

Part Number	Description
ACC-COMM-003	USB Communication Cable
ACCCAB-006	4 Pin Souriau Flying Input Lead – 1.5m
BATT-LD6	114Ah External Battery Pack
ACC-PRT-036	Wall Mounting Bracket
ACC-PRT-045	Meter Pit Hanging Bracket
ACC-ANT-009	External Antenna 0.5m cable
ACC-PRT-012	External Antenna Mounting Bracket
ACC-PRES-000	Curly/ Flexible Pressure Hose – 1.5m
ACC-PRES-003	1/8" Male BSP to Female Quick-fit Adapter

# Dimensions (mm)





